Diagram for the computation by the Engine of the Numbers of Bernoulli. See Note G. (page 44 *et seq.*)

Number of Operation.	Nature of Operation.	Variables acted upon.	Variables receiving results.	Indication of change in the value on any Variable.	Statement of Results.	Data.			Working Variables.										Result Variables.			
						$^1V_1$ ○ 0 0 0 1 [1]	$^1V_2$ ○ 0 0 0 2 [2]	$^1V_3$ ○ 0 0 0 4 [n]	$^0V_4$ ○ 0 0 0 0 [ ]	$^0V_5$ ○ 0 0 0 0 [ ]	$^0V_6$ ○ 0 0 0 0 [ ]	$^0V_7$ ○ 0 0 0 0 [ ]	$^0V_8$ ○ 0 0 0 0 [ ]	$^0V_9$ ○ 0 0 0 0 [ ]	$^0V_{10}$ ○ 0 0 0 0 [ ]	$^0V_{11}$ ○ 0 0 0 0 [ ]	$^0V_{12}$ ○ 0 0 0 0 [ ]	$^0V_{13}$ ○ 0 0 0 0 [ ]	$^1V_{21}$ ○ B_1 in a decimal fraction. [B_1]	$^1V_{22}$ ○ B_3 in a decimal fraction. [B_3]	$^1V_{23}$ ○ B_5 in a decimal fraction. [B_5]	$^0V_{24}$ ○ 0 0 0 [B_7]
1	×	$^1V_2 \times {}^1V_3$	$^1V_4, {}^1V_5, {}^1V_6$	$\left\{\begin{matrix} ^1V_2 = {}^1V_2 \\ ^1V_3 = {}^1V_3 \end{matrix}\right\}$	$= 2n$	...	2	n	$2n$	$2n$	$2n$											
2	−	$^1V_4 - {}^1V_1$	$^2V_4$	$\left\{\begin{matrix} ^1V_4 = {}^2V_4 \\ ^1V_1 = {}^1V_1 \end{matrix}\right\}$	$= 2n-1$	1	...	...	$2n-1$													
3	+	$^1V_5 + {}^1V_1$	$^2V_5$	$\left\{\begin{matrix} ^1V_5 = {}^2V_5 \\ ^1V_1 = {}^1V_1 \end{matrix}\right\}$	$= 2n+1$	1	...	...	...	$2n+1$												
4	÷	$^2V_5 \div {}^2V_4$	$^1V_{11}$	$\left\{\begin{matrix} ^2V_5 = {}^0V_5 \\ ^2V_4 = {}^0V_4 \end{matrix}\right\}$	$= \frac{2n-1}{2n+1}$	...	...	...	0	0	...	...	...	...	...	$\frac{2n-1}{2n+1}$						
5	÷	$^1V_{11} \div {}^1V_2$	$^2V_{11}$	$\left\{\begin{matrix} ^1V_{11} = {}^2V_{11} \\ ^1V_2 = {}^1V_2 \end{matrix}\right\}$	$= \frac{1}{2} \cdot \frac{2n-1}{2n+1}$	...	2	...	...	...	...	...	...	...	...	$\frac{1}{2} \cdot \frac{2n-1}{2n+1}$						
6	−	$^0V_{13} - {}^2V_{11}$	$^1V_{13}$	$\left\{\begin{matrix} ^2V_{11} = {}^0V_{11} \\ ^0V_{13} = {}^1V_{13} \end{matrix}\right\}$	$= -\frac{1}{2} \cdot \frac{2n-1}{2n+1} = A_0$	...	...	...	...	...	...	...	...	...	...	0	.....	$-\frac{1}{2} \cdot \frac{2n-1}{2n+1} = A_0$				
7	−	$^1V_3 - {}^1V_1$	$^1V_{10}$	$\left\{\begin{matrix} ^1V_3 = {}^1V_3 \\ ^1V_1 = {}^1V_1 \end{matrix}\right\}$	$= n-1\ (=3)$	1	...	n	...	...	...	...	...	...	$n-1$							
8	+	$^1V_2 + {}^0V_7$	$^1V_7$	$\left\{\begin{matrix} ^1V_2 = {}^1V_2 \\ ^0V_7 = {}^1V_7 \end{matrix}\right\}$	$= 2 + 0 = 2$	...	2	...	...	...	...	2										
9	÷	$^1V_6 \div {}^1V_7$	$^3V_{11}$	$\left\{\begin{matrix} ^1V_6 = {}^1V_6 \\ ^0V_{11} = {}^3V_{11} \end{matrix}\right\}$	$= \frac{2n}{2} = A_1$	...	...	...	...	...	$2n$	2	...	...	...	$\frac{2n}{2} = A_1$						
10	×	$^1V_{21} \times {}^3V_{11}$	$^1V_{12}$	$\left\{\begin{matrix} ^1V_{21} = {}^1V_{21} \\ ^3V_{11} = {}^3V_{11} \end{matrix}\right\}$	$= B_1 \cdot \frac{2n}{2} = B_1 A_1$	...	...	...	...	...	...	...	...	...	...	$\frac{2n}{2} = A_1$	$B_1 \cdot \frac{2n}{2} = B_1 A_1$	.....	B_1			
11	+	$^1V_{12} + {}^1V_{13}$	$^2V_{13}$	$\left\{\begin{matrix} ^1V_{12} = {}^0V_{12} \\ ^1V_{13} = {}^2V_{13} \end{matrix}\right\}$	$= -\frac{1}{2} \cdot \frac{2n-1}{2n+1} + B_1 \cdot \frac{2n}{2}$	...	...	...	...	...	...	...	...	...	...	.....	0	$\left\{-\frac{1}{2} \cdot \frac{2n-1}{2n+1} + B_1 \cdot \frac{2n}{2}\right\}$				
12	−	$^1V_{10} - {}^1V_1$	$^2V_{10}$	$\left\{\begin{matrix} ^1V_{10} = {}^2V_{10} \\ ^1V_1 = {}^1V_1 \end{matrix}\right\}$	$= n-2\ (=2)$	1	...	...	...	...	...	...	...	...	$n-2$							
13	−	$^1V_6 - {}^1V_1$	$^2V_6$	$\left\{\begin{matrix} ^1V_6 = {}^2V_6 \\ ^1V_1 = {}^1V_1 \end{matrix}\right\}$	$= 2n-1$	1	...	...	...	...	$2n-1$											
14	+	$^1V_1 + {}^1V_7$	$^2V_7$	$\left\{\begin{matrix} ^1V_1 = {}^1V_1 \\ ^1V_7 = {}^2V_7 \end{matrix}\right\}$	$= 2 + 1 = 3$	1	...	...	...	...	...	3										
15	÷	$^2V_6 \div {}^2V_7$	$^1V_8$	$\left\{\begin{matrix} ^2V_6 = {}^2V_6 \\ ^2V_7 = {}^2V_7 \end{matrix}\right\}$	$= \frac{2n-1}{3}$	...	...	...	...	...	$2n-1$	3	$\frac{2n-1}{3}$									
16	×	$^1V_8 \times {}^3V_{11}$	$^4V_{11}$	$\left\{\begin{matrix} ^1V_8 = {}^0V_8 \\ ^3V_{11} = {}^4V_{11} \end{matrix}\right\}$	$= \frac{2n}{2} \cdot \frac{2n-1}{3}$	...	...	...	...	...	...	...	0	...	...	$\frac{2n}{2} \cdot \frac{2n-1}{3}$						
17	−	$^2V_6 - {}^1V_1$	$^3V_6$	$\left\{\begin{matrix} ^2V_6 = {}^3V_6 \\ ^1V_1 = {}^1V_1 \end{matrix}\right\}$	$= 2n-2$	1	...	...	...	...	$2n-2$											
18	+	$^1V_1 + {}^2V_7$	$^3V_7$	$\left\{\begin{matrix} ^2V_7 = {}^3V_7 \\ ^1V_1 = {}^1V_1 \end{matrix}\right\}$	$= 3 + 1 = 4$	1	...	...	...	...	...	4										
19	÷	$^3V_6 \div {}^3V_7$	$^1V_9$	$\left\{\begin{matrix} ^3V_6 = {}^3V_6 \\ ^3V_7 = {}^3V_7 \end{matrix}\right\}$	$= \frac{2n-2}{4}$	...	...	...	...	...	$2n-2$	4	...	$\frac{2n-2}{4}$	...	$\left\{\frac{2n}{2} \cdot \frac{2n-1}{3} \cdot \frac{2n-2}{3} = A_3\right\}$						
20	×	$^1V_9 \times {}^4V_{11}$	$^5V_{11}$	$\left\{\begin{matrix} ^1V_9 = {}^0V_9 \\ ^4V_{11} = {}^5V_{11} \end{matrix}\right\}$	$= \frac{2n}{2} \cdot \frac{2n-1}{3} \cdot \frac{2n-2}{4} = A_3$	...	...	...	...	...	...	...	...	0								
21	×	$^1V_{22} \times {}^5V_{11}$	$^0V_{12}$	$\left\{\begin{matrix} ^1V_{22} = {}^1V_{22} \\ ^0V_{12} = {}^2V_{12} \end{matrix}\right\}$	$= B_3 \cdot \frac{2n}{2} \cdot \frac{2n-1}{3} \cdot \frac{2n-2}{3} = B_3 A_3$	...	...	...	...	...	...	...	...	...	...	0	$B_3 A_3$	.....	.....	B_3		
22	+	$^2V_{12} + {}^2V_{13}$	$^3V_{13}$	$\left\{\begin{matrix} ^2V_{12} = {}^0V_{12} \\ ^2V_{13} = {}^3V_{13} \end{matrix}\right\}$	$= A_0 + B_1 A_1 + B_3 A_3$	...	...	...	...	...	...	...	...	...	...	.....	0	$\left\{A_3 + B_1 A_1 + B_3 A_3\right\}$				
23	−	$^2V_{10} - {}^1V_1$	$^3V_{10}$	$\left\{\begin{matrix} ^2V_{10} = {}^3V_{10} \\ ^1V_1 = {}^1V_1 \end{matrix}\right\}$	$= n-3\ (=1)$	1	...	...	...	...	...	...	...	...	$n-3$							
Here follows a repetition of Operations thirteen to twenty-three.																						
24	+	$^4V_{13} + {}^0V_{24}$	$^1V_{24}$	$\left\{\begin{matrix} ^4V_{13} = {}^0V_{13} \\ ^0V_{24} = {}^1V_{24} \end{matrix}\right\}$	$= B_7$	...	...	...	...	...	...	...	...	...	...	.....	.....	.....	.....	.....	.....	B
25	+	$^1V_1 + {}^1V_3$	$^1V_3$	$\left\{\begin{matrix} ^1V_1 = {}^1V_1 \\ ^1V_3 = {}^1V_3 \\ ^5V_6 = {}^0V_6 \\ ^5V_7 = {}^0V_7 \end{matrix}\right\}$	$= n+1 = 4+1 = 5$ by a Variable-card. by a Variable-card.	1	...	$n+1$	...	...	0	0										